

006260-9462950

AS
Cost

--13. A signal transmission and reception apparatus for transmitting and receiving a VSB signal, said transmission and reception apparatus comprising a transmission apparatus and a reception apparatus,

said transmission apparatus being for use with a source signal having a first data stream and a second data stream, said transmission apparatus comprising:

an error correction encoder operable to trellis encode the second data stream;

a modulator operable to modulate the first data stream and the second data stream, such that the number of signal points of the first data stream in a signal space is different from the number of signal points of the second data stream in the signal space and such that the first data stream has data for demodulation including information representing the number of signal points of the second data stream in a signal space and such that the number of signal points of the first data stream is equal to or less than 4, to produce a VSB modulation signal, said modulator comprising an allocator operable to allocate code points along a uniaxial modulation coordinate system, and a filter, having a plurality of coefficients which are a series of impulse responses defined by plotting time base responses to the VSB modulation signal along the in-phase axis and its orthogonal axis, operable to filter a series of the code points allocated along the uniaxial modulation coordinate system; and

a transmitter operable to transmit the VSB modulation signal;

said reception apparatus comprising:

a receiver operable to receive a transmitted VSB modulation signal;

006250" 94522350

A2
Cont

a demodulator operable to demodulate the VSB modulation signal, received by said receiver, into the first and second data streams, and to demodulate the second data stream according to the data for demodulation in the first data stream; and

an error correction decoder operable to trellis decode the second data stream.

14. A signal transmission apparatus for transmitting a VSB signal, for use with a source signal having a first data stream and a second data stream, said signal transmission apparatus comprising:

an error correction encoder operable to trellis encode the second data stream;

a modulator operable to modulate the first data stream and the second data stream, such that the number of signal points of the first data stream in a signal space is different from the number of signal points of the second data stream in the signal space and such that the first data stream has data for demodulation including information representing the number of signal points of the second data stream in a signal space and such that the number of signal points of the first data stream is equal to or less than 4, to produce a VSB modulation signal, said modulator comprising an allocator operable to allocate code points along a uniaxial modulation coordinate system, and a filter, having a plurality of coefficients which are a series of impulse responses defined by plotting time base responses to the VSB modulation signal along the in-phase axis and its orthogonal axis, operable to filter a series of the code points allocated along the uniaxial modulation coordinate system; and

005260" 94622960

a transmitter operable to transmit the VSB modulation signal.

- ✓ 15. A signal reception apparatus comprising:
a receiver operable to receive a transmitted VSB modulation
signal having information of a first data stream and a second data
stream, wherein the number of signal points of the first data stream
assigned in a signal space is different from the number of signal points
of the second data stream in the signal space, the first data stream has
data for demodulation including information representing the number
of signal points of the second data stream in a signal space, and the
number of signal points of the first data stream is equal to or less than

4;

a demodulator operable to demodulate the VSB modulation
signal into the first and second data streams, and to demodulate the
second data stream according to the data for demodulation in the first
data stream; and

an error correction decoder operable to trellis decode the
second data stream.

- ✓ 16. A signal transmission and reception method for transmitting
and receiving a VSB signal, said signal transmission and reception
method being for use with a source signal having a first data stream
and a second data stream, said transmission and reception method
comprising:

trellis encoding the second data stream;

modulating the first data stream and the second data stream,
such that the number of signal points of the first data stream in a signal
space is different from the number of signal points of the second data

006260" 94627960

Ag
Cont

stream in the signal space and such that the first data stream has data for demodulation including information representing the number of signal points of the second data stream in a signal space and such that the number of signal points of the first data stream is equal to or less than 4, to produce a VSB modulation signal;

allocating code points along a uniaxial modulation coordinate system;

filtering, with a filter having a plurality of coefficients which are a series of impulse responses defined by plotting time base responses to the VSB modulation signal along the in-phase axis and its orthogonal axis, a series of the code points allocated along the uniaxial modulation coordinate system;

transmitting the VSB modulation signal;

receiving the transmitted VSB modulation signal;

demodulating the VSB modulation signal into the first and second data streams and demodulating the second data stream according to the demodulation information in the first data stream;
and

trellis decoding the second data stream.

17. A signal transmission method for transmitting a VSB signal, for use with a source signal having a first data stream and a second data stream, said signal transmission method comprising:

trellis encoding the second data stream;

modulating the first data stream and the second data stream, such that the number of signal points of the first data stream in a signal space is different from the number of signal points of the second data stream in the signal space and such that the first data stream has data

005260" 94622960

A2
Correct

for demodulation including information representing the number of signal points of the second data stream in a signal space and such that the number of signal points of the first data stream is equal to or less than 4, to produce a VSB modulation signal;

allocating code points along a uniaxial modulation coordinate system;

filtering, with a filter having a plurality of coefficients which are a series of impulse responses defined by plotting time base responses to the VSB modulation signal along the in-phase axis and its orthogonal axis, a series of the code points allocated along the uniaxial modulation coordinate system; and

transmitting the VSB modulation signal.

18. A signal reception method comprising:

receiving a transmitted VSB modulation signal having information of a first data stream and a second data stream, wherein the number of signal points of the first data stream assigned in a signal space is different from the number of signal points of the second data stream in the signal space, the first data stream has data for demodulation including information representing the number of signal points of the second data stream in a signal space, and the number of signal points of the first data stream is equal to or less than 4;

demodulating the VSB modulation signal into the first and second data streams, and demodulating the second data stream according to the demodulation information in the first data stream;
and

trellis decoding the second data stream.--